

KUSAM-MECO**FEATURES**

- Auto Ranging
- **Display** : 4000 counts (3¾ digits)
- Auto/Manual Measurement
- AC/DC Voltage
- Resistance
- Diode & Continuity Test
- Capacitance
- DC/AC A/mA/10A
- Frequency & Duty cycle
- Low battery indication
- **Measurement rate** : 3 times / sec.
- Data hold Function
- Auto Power Off.
- **Accessories** : Test Leads, Manual.

3¾ DIGIT**3999 COUNTS****DIGITAL****CLAMPMETER****MODEL - 2763.****ELECTRICAL SPECIFICATIONS:****DC VOLTAGE**

Range	Resolution	Accuracy
400 mV	0.1 mV	± (1% rdg + 3 dgts)
4 V	0.001 V	
40 V	0.01 V	
400 V	0.1 V	
1000 V	0.1 V	

Input Impedance : 10M

AC VOLTAGE (50 ~ 500Hz)

Range	Resolution	Accuracy
400 mV	0.1 mV	± (2.5% rdg + 5 dgts)
4 V	0.001 V	
40 V	0.01 V	
400 V	0.1 V	
750 V	1 V	

Input Impedance : 10M

RESISTANCE

Range	Resolution	Accuracy
400	0.1	± (1% rdg + 3 dgts)
4 k	0.001 k	
40 k	0.01 k	
400 k	0.1 k	
4 M	0.001 M	
40 M	0.01 M	± (3% rdg + 5 dgts)

CAPACITANCE

Range	Resolution	Accuracy
4 nF	0.001 nF	± (3% rdg + 3 dgts)
40 nF	0.01 nF	
400 nF	0.1 nF	
4 F	0.001 F	
40 F	0.01 F	
100 F	0.1 F	

FREQUENCY

Range	Resolution	Accuracy
40 Hz	0.01 Hz	± (0.3% rdg + 3 dgts)
400 Hz	0.1 Hz	
4 kHz	0.001 kHz	
40 kHz	0.01 kHz	
400 kHz	0.1 kHz	
4 MHz	0.001 MHz	

ACA (50 ~ 60Hz)

Range	Resolution	Accuracy
400 A	0.01 A	± (2.5% rdg + 4 dgts)
1000 A	1 A	

DC/AC A/mA/A

Range	Resolution	Accuracy
400 A	0.1 A	DC ± (1.5% rdg + 3 dgts)
4000 A	1.0 A	
40 mA	0.01 mA	
400 mA	0.1 mA	AC ± (3% rdg + 5 dgts)
10 A	0.01 A	

Industrial Supply Syndicate

54, Ezra Street, Kolkata - 700 001, India Phone: 033 32916080, 22356676 Fax: 30222923, 39851451

Email: info@industrialindia.com Website: www.industrialindia.com